



POWERING THE NATION

Since 1936

1300 555 253
dunlite.com.au

RELIABLE POWER FOR ANY SITUATION

Australian environment throws up plenty of challenges, so the last thing you want to worry about is a generator that slows you down or stops your work. At Dunlite, we understand this better than most. We've been powering Australia for over 80 years, which is why we don't cut corners when it comes to engineering our generators for reliability.

- For tough, continuous performance that won't let you down, we use genuine brands you know and trust such as Honda, Kohler, Yanmar and Lister Petter engines.
- We use premium quality engines & alternators to provide industry leading clean power, producing pure sine wave with less than 6% total harmonic distortion so you can use your Dunlite generator with even the most sensitive equipment.
- Our generators are rated conservatively so they will go that extra mile when you really need it.
- Parts and service are available Australia-wide, supported by a growing network of over 500 dealers.
- All Honda GX engines are covered by a 3 year (36 month) Honda warranty. Lister Petter portable petrol generators are covered by 1 year warranty (not including battery). Lister Petter, Yanmar & Kohler diesel engines are covered by 1 year warranty. All other engines and components are covered by a 2 year (24 month) warranty.

SIZING YOUR GENERATOR

There is a Dunlite generator to suit almost any need. Our range offers outputs from **2.8kVA (2300W) to 20kVA (16000W)**. Your dealer can help you choose the right generator for your needs, or you can use the table below as a guide.

Firstly, estimate the maximum '**Steady State Load**' – the total power required by all the lights, tools and appliances you expect to operate at any one time. For example; to operate a kettle (1500W), a hot water service (3000W) and two 100W lights, your Steady State Load will be 4700W or 4.7kW.

You should always choose a generator to match your maximum power demand.

Electric motors require more power to start than they do to run. If using electric motors, assume a maximum demand of three times the Steady State Load shown in the chart (ie; a 1hp motor will require 750W to operate but 2250W to start). Motors starting under load (e.g. compressors and submersible pumps) have higher starting demand. **Dunlite generators are rated in both Watts and kVA** (at 0.8 Power Factor (PF)).

Note the above example calculations and table are provided as a guide only. The power demand of appliances varies with brands and models. If in doubt, please consult your dealer for assistance.

Appliance	Watts
Air Conditioner (evaporative)	275
Air Conditioner (refrigerative)	750 - 2,500
Clothes Dryer	2,400
Computer	30 - 250
Domestic Water Pump (½ hp)	375
Electric Motor	
- ½ hp	375
- 1 hp	750
- 2 hp	1,500
Grinder (9")	2,300
Hot Water Service	2,500 - 3,500
Kettle or Jug	800 - 1,500
Lights	25 - 200
Microwave Oven	500 - 1,200
Refrigerator	100 - 800
Television Set	75 - 200
Toaster	250 - 1,250
Vacuum Cleaner	250 - 1,200
Washing Machine	500 - 3,000
Welder (140 Amps)	4,000

OPTIONAL ACCESSORIES



- RCD Earth Leakage Protection
- Automatic Transfer Switch
- Generator Covers – Small and Large
- Wheel, Wheel Barrow Kits & Lifting Bars
- Remote Stop / Start Kits
- Long Range Fuel Tank
- Wheel Kits for Large Generators
- Welding Leads



RELIABLE POWER FOR ANY SITUATION



GENERATORS 2.8kVA TO 20kVA Tough and portable, our generators will meet your needs at home, in the shed, on the back of the ute or in the worksite. For more demanding situations, our range generators will give you extra power without blowing the budget. The bigger units will run a wool press on the farm, a welder on a building site or a decent air conditioner with ease. These generators are powered by **Honda, Yanmar, Kohler or Lister Petter** in either **Petrol or Diesel**, and available in recoil for the smaller models or electric start for the larger models.



LISTER PETTER PORTABLE PETROL GENERATORS From a brand internationally known for high quality & reliable engines, comes a range of portable petrol generators that you can depend on. Lister Petter portable generators pack a lot of power in compact footprint, making it a portable & economical choice for your worksite. These units come with **electric start, AVR, fuel & voltage meter, handle & wheels. Battery is included.**




WELDER GENERATORS & MULTI POWER PACKS (4-IN-1 UNITS) Our welder generators have been designed to get the job done without a hitch, offering 7kVA of real power. For full flexibility the Multi Power Pack is the answer. With **7kVA of continuous power** and welding capacity of **200 Amps**, these machines just work. Complete with a welder, generator, air compressor and battery charger. Available in recoil or electric start and powered by a Honda engine, you can't go wrong with these work horses. Welding leads are also available as an optional extra.



RCD GENERATORS Packed full of extras, this range is ideal for the work site and trade industry. With everything a tradie needs including work **safe RCD protected outlets** which is now an **Australian Standard** safety requirement on all building sites. With the optional kit which includes wheels, handles and centre point lift, they are a must-have generator for the roaming tradie.



TRACTOR PACKS Having dedicated back-up generators in a farm situation is rarely affordable, however you can protect your income by combining your tractor with one of Dunlite's power-take-off driven alternators (**Tractor Packs**) for a ready-made source of power should the mains go down during milking or at another critical time. Ranging from **50kVA to 100kVA** and fitted with **a splined shaft** accepting an **input speed of 500rpm**, our Tractor Packs couple to most brands of tractor.



MINE SPEC GENERATORS Dunlite offer a range of mine spec generators specifically built to meet strict mine site requirements. Ranging in size from **6.8kVA (5400W) to 8.5kVA (6800W)**, these portable units include **a detachable fire extinguisher, battery isolator switch, individual lockable RCD switches, 15 Amp weather protected outlets, emergency stop button, bunded fuel tank with lockable cap and a centre point lifting bar** for easy transportation. So you can rest assured you will get the job done with safety as a priority.

DUNLITE GENERATORS

Model	Power Rating	Engine Model	Continuous Output	Noise Level @ 7 Metres	Start Method	Fuel Tank Capacity	Operation Hrs @ 80% Load	Dimensions (LxWxH) mm	Dry Weight
LISTER PETER PORTABLE PETROL GENERATORS									
Electric Start, AVR, Fuel Meter, Voltage Meter, AC Circuit Breaker. Includes Transport Kit (handles & wheels). Battery included.									
LPP3.5RE	3.5 kVA	Lister SFE200	2500W	68 dBA	Recoil/Electric	15L	11.5 hrs	625x460x465	52.2 kg
LPP8RE	8 kVA	Lister SFE440	6000W	72 dBA	Recoil/Electric	25L	7.5 hrs	705x540x580	102 kg
GENERATORS (PETROL POWERED) UNDER 9kVA									
DGUH2.3S-2	2.8 kVA	Honda GP200	2300W	67 dBA	Recoil	3.1L	2.32 hrs	650x460x415	40 kg
DGUH2.7S-2	3.3 kVA	Honda GX200	2700W	67 dBA	Recoil	3.1L	2.32 hrs	650x460x415	40 kg
DGUH5S-2	5.8 kVA	Honda GX340	4800W	68 dBA	Recoil	6.1L	2.60 hrs	810x545x545	70 kg
DGUH5ES-2	5.8 kVA	Honda GX340	4800W	68 dBA	Recoil/Electric	6.1L	2.60 hrs	810x545x545	75 kg
DGUH6S-2	7 kVA	Honda GX390	5600W	69 dBA	Recoil	6.1L	2.50 hrs	810x545x545	75 kg
DGUH6ES-2	7 kVA	Honda GX390	5600W	69 dBA	Recoil/Electric	6.1L	2.50 hrs	810x545x545	80 kg
DGUH6.5-3S-2	7 kVA	Honda GX390	6000W/3 Phase	69 dBA	Recoil	6.1L	2.50 hrs	810x545x545	80 kg
DGUH6.5E-3S-2	7 kVA	Honda GX390	6000W/3 Phase	69 dBA	Recoil/Electric	6.1L	2.50 hrs	810x545x545	85 kg
DGUH7S-2	8 kVA	Honda GX390	6500W	72 dBA	Recoil	6.1L	2.36 hrs	810x545x545	80 kg
DGUH7ES-2	8 kVA	Honda GX390	6500W	72 dBA	Recoil/Electric	6.1L	2.36 hrs	810x545x545	85 kg
DGUH7ES-2-R/S	8 kVA	Honda GX390	6500W	70 dBA	Recoil/Electric	30L	11.6 hrs	800x545x575	120 kg
GENERATORS (PETROL POWERED) 9kVA TO 16kVA WITH LONG RANGE FUEL TANK									
DGUH9ES-2	9.5 kVA	Honda GX630	7500W	75 dBA	Electric	34L	6.15 hrs	876x546x700	110 kg
DGUH11ES-2	11 kVA	Honda GX630	8000W	75 dBA	Electric	34L	6.15 hrs	876x546x700	110 kg
DGUH11E-3S-2	12 kVA	Honda GX630	9600W/3 Phase	75 dBA	Electric	34L	6.15 hrs	876x546x700	130 kg
DGUH15ES-2	15 kVA	Honda GX690	12000W	75 dBA	Electric	34L	5.66 hrs	876x546x700	160 kg
DGUH16E-3S-2	16 kVA	Honda GX690	12000W/3 Phase	75 dBA	Electric	34L	5.66 hrs	876x546x700	165 kg
DGUH20ES-2	20 kVA	Honda iGX800	16000W	75 dBA	Electric	34L	6.15 hrs	880x550x710	165 kg
RCD GENERATORS									
RCD model includes 2 x 15 Amp IP56 RCD Protected Outlets									
DGUH2.7S-2-RCD	3.3 kVA	Honda GX200	2700W	67 dBA	Recoil	3.1L	2.32 hrs	650x460x415	40 kg
DGUH7S-2-RCD2	8 kVA	Honda GX390	6500W	72 dBA	Recoil	6.1L	2.36 hrs	710x570x560	90 kg
With optional wheels, handles & lifting bar kit.									
AVR CONTROLLED GENERATORS (PETROL POWERED)									
DGUH7C-2A	8 kVA	Honda GX390	6500W	72 dBA	Recoil	6.1L	2.36 hrs	810x545x545	82kg
DGUH7EC-2A	8 kVA	Honda GX390	6500W	72 dBA	Recoil/Electric	6.1L	2.36 hrs	810x545x545	87kg
DGUH10EC-2A	10 kVA	Honda GX630	8000W	75 dBA	Electric	34L	6.15 hrs	876x545x700	113kg
WELDER GENERATORS									
Welder Duty Cycle: 200 Amps @ 60%									
DGWGH7S-2	7 kVA	Honda GX390	6000W/200 Amp	69 dBA	Recoil	6.1L	2.5 hrs	810x545x545	100 kg
DGWGH7ES-2	7 kVA	Honda GX390	6000W/200 Amp	69 dBA	Recoil/Electric	6.1L	2.5 hrs	810x545x545	105 kg
MULTI-POWER PACKS									
240V Compressor: 14 cfm, Air Tank Capacity: 50L, Welder: 200 Amp @ 60% (AC Welding), Battery Charger: 10 Amps, 12/24 V (DC Charging)									
MPP	7 kVA	Honda GX390	6000W/200 Amp	69 dBA	Recoil	6.1L	2.5 hrs	900x870x680	105 kg
MPPE	7 kVA	Honda GX390	6000W/200 Amp	69 dBA	Recoil/Electric	6.1L	2.5 hrs	900x870x680	110 kg
GENERATORS (DIESEL POWERED)									
DGUYD6.8ES-2	6.8 kVA	Yanmar L100N5	5400W	80 dBA	Recoil/Electric	5.4L	3.3 hrs	810x545x545	101 kg
DGUYD6.8E-3S-2	6.8 kVA	Yanmar L100N5	5400W/3 Phase	80 dBA	Recoil/Electric	5.4L	3.3 hrs	810x545x545	101 kg
DGULD7ES-2	7 kVA	Lister LPDR188	5600W	80 dBA	Recoil/Electric	5L	3 hrs	810x545x545	110 kg
DGULD7E-3S-2	7 kVA	Lister LPDR188	5600W/3 Phase	80 dBA	Recoil/Electric	5L	3 hrs	810x545x545	110 kg
DGULD7.7ES-2	7.7	Lister LPDR192	6160W	80 dBA	Recoil/Electric	5L	3 hrs	810x545x545	117 kg
DGUKD8.5ES-2	8.5 kVA	Kohler KD425	6800W	80 dBA	Recoil/Electric	34L	13 hrs	876x546x700	165 kg
MINE SPEC GENERATORS (DIESEL POWERED)									
Detachable Fire Extinguisher, Battery Isolator Switch, Individual lockable RCD Switches, 15 Amp weather protected outlets, Emergency Stop button, Bundled fuel tank & lockable cap, Centre point lift bar									
DGUYD6.8ES-MINE	6.8 kVA	Yanmar L100N5	5400W	80 dBA	Recoil/Electric	36L	21 hrs	876x546x700	165 kg
DGULD7ES-MINE	7 kVA	Lister LPDR188	5600W	80 dBA	Recoil/Electric	36L	21.6 hrs	876x546x700	165 kg
DGUKD8.5ES-MINE	8.5 kVA	Kohler KD425	6800W	80 dBA	Recoil/Electric	36L	13.8 hrs	876x546x700	172 kg
Specifications subject to variation without notice. Images for illustration purposes only. Product may vary from image.									



1300 555 253
dunlite.com.au

POWERED by
HONDA

YANMAR KOHLER

